



# ENAPART



93 S Railroad Avenue Unit C  
Bergenfield NJ 07621 USA  
[www.enapart.com](http://www.enapart.com)  
[sales@enapart.com](mailto:sales@enapart.com)



Via del Canneto 35,  
Borgosatollo, Brescia - Italia  
[www.enapart.it](http://www.enapart.it)  
[vendite@enapart.it](mailto:vendite@enapart.it)



Barbaros Mah. Ihlamur Bul. Aĝaoĝlu  
My Newwork No:3/15 Ataşehir / İstanbul  
[www.enapart.net](http://www.enapart.net)  
[satis@enapart.net](mailto:satis@enapart.net)



PRIVADA 10 B SUR #3908 COL.  
ANZUREZ, C.P. 72530, PUEBLA, PUE  
[www.enapart.com.mx](http://www.enapart.com.mx)  
[sales@enapart.com.mx](mailto:sales@enapart.com.mx)



Friedrich-Ebert-Anlage 36, 60325  
Frankfurt am Main, Germany  
[www.enapart.de](http://www.enapart.de)  
[anfrage@enapart.de](mailto:anfrage@enapart.de)



4 boulevard Carnot, 95400  
villiers-le-bel, Paris, France  
[www.enapart.fr](http://www.enapart.fr)  
[sales@enapart.fr](mailto:sales@enapart.fr)



65049, ОДЕСА, ВУЛИЦЯ ІВАНА  
ФРАНКА, БУДИНОК 55, ПОВЕРХ 3  
[www.enapart.com.ua](http://www.enapart.com.ua)  
[sales@enapart.com.ua](mailto:sales@enapart.com.ua)



MUNICIPIUL BUCUREȘTI, SECTOR 3,  
B-DUL BASARABIA, NR.250, CORP P+5  
[www.enapart.ro](http://www.enapart.ro)  
[sales@enapart.ro](mailto:sales@enapart.ro)



〒584-0023 大阪府富田林市若松町  
東2丁目2番16号  
[www.enapart.co.jp](http://www.enapart.co.jp)  
[sales@enapart.co.jp](mailto:sales@enapart.co.jp)



PLAZA NUESTRA SEÑORA DE LAS  
NIEVES 12 ,LOCAL ,50012,ZARAGOZA  
[www.enapart.es](http://www.enapart.es)  
[ventas@enapart.es](mailto:ventas@enapart.es)



Складова база „Онгъл“, Склад А2, п.к.  
4006, гр. Пловдив, България  
[www.enapart.bg](http://www.enapart.bg)  
[sales@enapart.bg](mailto:sales@enapart.bg)



3 Austin Mews, High Street, Hemel  
Hempstead, HP1 3AF , United Kingdom  
[www.enapart.co.uk](http://www.enapart.co.uk)  
[sales@enapart.co.uk](mailto:sales@enapart.co.uk)

Code	792.3.275-334
Voltage (V)	120 VAC
Frequency (Hz)	50 Hz
Customer	
Working Order Number	691670
Request Number	7-2015
Number	No.1
Test Date&Time	26.01.2015 09:16:30
Description	1 stage / tangential
Stator	65 / 0,75
Rotor	
Controler	792.2.545
Weight	2,4 kg
Remarks	
Source Results File	\\DomeInt.local\fs\ECM\Merjenje_karakteristik\Vzorci 2015\7-2015VCMP792.3.275-334No.1_26.01.2015_09.16.30691670.tdms

Ambient temperature [°C]=  Humidity [%]=  Absolute pressure [kPa]=  Warmup time [min]=  Tout [°C]=

Orifice (mm)	Current I1 (A)	Input Power (W)	Speed (/min)	Vacuum (kPa)	Air Flow (dm <sup>3</sup> /s)	Air Power (W)	Efficiency (%)
60,0	6,5	463,7	13866,2	1,2	73,8	85,3	18,4
50,0	6,4	453,3	13987,0	1,8	64,5	118,6	26,2
40,0	6,0	417,2	14379,2	2,7	50,2	137,0	32,8
30,0	5,3	364,3	14985,5	3,6	32,5	117,2	32,2
23,0	4,8	318,2	15541,8	4,1	20,5	84,7	26,6
21,0	4,6	304,7	15719,8	4,3	17,4	74,4	24,4
19,0	4,4	292,9	15857,2	4,4	14,4	63,0	21,5
16,0	4,3	278,0	16032,5	4,5	10,4	46,6	16,7
13,0	4,0	262,3	16209,2	4,6	7,0	32,3	12,3
10,0	3,7	232,1	16419,0	4,8	4,2	20,4	8,8
6,5	3,5	219,1	16531,8	4,9	1,8	9,0	4,1
0,0	3,3	209,6	16615,8	5,0	0,0	0,0	0,0

Normal operation according to IEC 60355-2-2:

Pf (W)=   
 Pi (W)=   
 Pm (W)=

Last Minute Comment:

Test engineer:

At orifice  measured after  seconds

Maximum measured values:

Input power=  W Air power=  W Vacuum=  kPa Air flow=  dm<sup>3</sup>/s Efficiency=  %

